

Application Note

Adbun-M4NR User Guide

Arm and Keil are registered trademarks of Arm Limited (or its subsidiaries) in the US and/or elsewhere.

All other company names, product names, and service names mentioned herein may be trademarks of their respective companies.

Table of Contents

Table of Contents	2
1. Preface.....	4
2. Technical Term.....	4
3. Reference Document.....	4
4. Operation Confirmation Condition.....	5
5. Used Channel and Port Assignment	5
5.1. User Interface	5
5.1.1. Push-Switch	5
5.1.2. LED	5
5.2. Communication.....	5
5.2.1. UART Communication.....	5
5.2.2. FUART Communication	6
5.2.3. TSSI Communication	6
5.2.4. TSPI Communication	6
5.2.5. I2C Communication.....	6
5.2.6. EI2C Communication	7
5.2.7. I2S Communication	7
5.2.8. SMIF Communication	7
5.2.9. CAN Communication	7
5.2.10. ETHM Communication	7
5.3. Timer	8
5.4. DAC	8
5.5. ADC	8
5.6. RMC.....	8
5.7. HDMAC.....	8
5.8. MDMAC	8
5.9. ISD.....	8
6. System Setting	8
7. Communication Setting	9
7.1. UART Communication Setting	9
7.2. I2C Communication Setting.....	9
7.3. SPI Communication Setting	9
7.4. EI2C.....	9
7.5. FUART	9
7.6. I2S	9
7.7. TSPI.....	9
7.8. TSSI.....	9
7.9. ETHM.....	10
8. Precautions for use.....	11

9. Revision History 11
RESTRICTIONS ON PRODUCT USE.....12

1. Preface

This application note can be used as a reference of use environment when the sample program is operated on the Adbun-M4NR evaluation board.

When other MCU's than TPM4GR are selected, a compilation error may occur due to source shortage of pins or IP channels. When the error occurs, the program should be fixed, then the operation should be checked.

2. Technical Term

Term/Abbreviation	Definition
BSP	Board Support Package
UART	Universal Asynchronous Receiver Transmitter
FUART	Full Universal Asynchronous Receiver Transmitter
LED	Light-emitting diode
TSPI	Toshiba Serial Peripheral Interface
TSSI	Toshiba Synchronous Serial Interface
I2C	Inter-Integrated Circuit
EI2C	Enhanced Inter-Integrated Circuit
ADC	Analog to Digital Converter
DAC	Digital to Analog Converter
CAN	Controller Area Network
SMIF	Serial Memory Interface
ETHM	EthernetMAC
ISD	Interval Sensing Detector
RMC	Remote control Signal preprocessor
HDMAC	High speed Direct Memory Access Controller
MDMAC	Multi function DMAC

3. Reference Document

Document Name	Notes
TMPM4N Group(1) Data sheet	-
Reference manual	Refer to the reference manual of each IP to be used.
Application note	Refer to the application note of sample software to be used.

4. Operation Confirmation Condition

Item	Name	Version
Used Microcontroller	TMPM4NRF20FG	-
Used Board	Adbun-M4NR	-
Unified Development Environment	IAR Embedded Workbench for ARM	8.50.1.24811
Unified Development Environment	Arm® Keil® MDK	5.29.00
Sample Program	TMPM4NR_v150	V1.5.0

5. Used Channel and Port Assignment

5.1. User Interface

5.1.1. Push-Switch

Channel	Function	Port
BSP_PSW_0	Input	PP2
BSP_PSW_1	Input	PP3
BSP_PSW_2	Input	PP4
BSP_PSW_3	Input	PP5
BSP_PSW_4	Input	PL0

5.1.2. LED

Channel	Function	Port
BSP_LED_0	Output	PW4
BSP_LED_1	Output	PW5
BSP_LED_2	Output	PW6
BSP_LED_3	Output	PW7

5.2. Communication

5.2.1. UART Communication

Channel	Peripheral Channel	Function	Port
BSP_UART_0	ch0	UT0TXD	PE3
		UT0RXD	PE2
		UT0CTS	—
		UT0RTS	—
BSP_UART_1	ch5	UT5TXD	PJ0
		UT5RXD	PJ1
		UT5CTS	—
		UT5RTS	—
BSP_UART_2	ch1	UT1TXD	PH0
		UT1RXD	PH1
		UT1CTS	—
		UT1RTS	—

5.2.2. FUART Communication

Channel	Peripheral Channel	Function	Port
BSP_FUART_0	ch0	FUT0TXD	PJ4
		FUT0RXD	PJ5
		FUT0CTS	—
		FUT0RTS	—
		FUT0IROUT	—
		FUT0IRIN	—

5.2.3. TSSI Communication

Channel	Peripheral Channel	Function	Port
BSP_TSSI_0	ch0	TSSI0TCK	PD2
		TSSI0TFS	PD3
		TSSI0TXD	PD4
		TSSI0RCK	—
		TSSI0RFS	—
		TSSI0RXD	—
BSP_TSSI_1	ch1	TSSI1TCK	—
		TSSI1TFS	—
		TSSI1TXD	—
		TSSI1RCK	PU7
		TSSI1RFS	PU6
		TSSI1RXD	PU5

5.2.4. TSPI Communication

Channel	Peripheral Channel	Function	Port
BSP_TSPI_0	ch2	TSPI2CSIN	—
		TSPI2CS0	PA7
		TSPI2CS1	—
		TSPI2CS2	—
		TSPI2CS3	—
		TSPI2RXD	PA5
		TSPI2TXD	PA4
		TSPI2SCK	PA6
BSP_TSPI_1	ch4	TSPI4CSIN	PD0
		TSPI4CS0	—
		TSPI4CS1	—
		TSPI4CS2	—
		TSPI4CS3	—
		TSPI4RXD	PD2
		TSPI4TXD	—
		TSPI4SCK	PD1

5.2.5. I2C Communication

Channel	Peripheral Channel	Function	Port
BSP_I2C_0	ch3	I2C3SDA	PJ6
		I2C3SCL	PJ7

5.2.6. EI2C Communication

Channel	Peripheral Channel	Function	Port
BSP_EI2C_0	ch3	EI2C3SDA	PJ6
		EI2C3SCL	PJ7

5.2.7. I2S Communication

Channel	Peripheral Channel	Function	Port
BSP_I2S_0	ch0	I2S0BCK	PD5
		I2S0LRCK	PD4
		I2S0D0	PD7

5.2.8. SMIF Communication

Channel	Peripheral Channel	Function	Port
BSP_SMIF_0	ch0	SMI0D0	PK2
		SMI0D1	PK3
		SMI0D2	PK4
		SMI0D3	PK5
		SMI0SCK	PK6
		SMI0CS0_N	PK7

5.2.9. CAN Communication

Channel	Peripheral Channel	Function	Port
BSP_CAN_0	ch0	CAN1TX	PU7
		CAN1RX	PU6

5.2.10. ETHM Communication

Channel	Peripheral Channel	Function	Port
BSP_ETHM_0	ch0	EMACRS	PG2
		EMACOL	PG3
		EMAMDC	PG7
		EMAMDIO	PH0
		EMATXD0	PM3
		EMATXD1	PM2
		EMATXD2	PM1
		EMATXD3	PM0
		EMATXCLK	PT4
		EMATXEN	PK0
		EMARXD0	PL2
		EMARXD1	PL3
		EMARXD2	PG4
		EMARXD3	PG5
		EMARXCLK	PL1
		EMARXER	PG1
		EMARXDV	PG0

5.3. Timer

Channel	Peripheral Channel	Function	Port
BSP_TIMER_1MS	ch0	1 ms timer	—
BSP_OUT_PULSE_SAMPLE_A	ch2	PPG output	PB2
BSP_T32A_REFIN	ch8	Reference signal input(TRM)	PB0

5.4. DAC

Channel	Peripheral Channel	Function	Port
BSP_DAC_0	ch0	DAC0	PT0

5.5. ADC

Channel	Peripheral Channel	Function	Port
BSP_ADC_0	AINA8	Variable resistance voltage	PP0

*ADC_UART and ADC_MONITOR do sample A operation.

5.6. RMC

Channel	Peripheral Channel	Function	Port
BSP_RMC_0	ch0	RXIN0	PT3

5.7. HDMAC

Channel	Peripheral Channel	Function	Port
BSP_HDMAC_0	ch0	High-speed DMA controller	—

5.8. MDMAC

Channel	Peripheral Channel	Function	Port
BSP_MDMAC_0	ch7	Multifunctional DMA controller	—
BSP_MDMAC_1	ch9	Multifunctional DMA controller	—

5.9. ISD

Channel	Peripheral Channel	Function	Port
BSP_ISD_0	UNIT B	Interval Sensor Detection Circuit	—

6. System Setting

Clock	Function	MHz	Notes
fEHOSC	External oscillator	12	-
fIHOSC	Internal oscillator	10	-
fs	Low-speed oscillator	0.032768	-
fc	High-speed clock	192	-
fsys	System clock	192	-
φT0	φT0	120	-

*It's basic setting. Settings change depending on the sample software.

7. Communication Setting

7.1. UART Communication Setting

Item	Setting Value	Notes
Baud Rate	115200 bps	-
Data Length	8 bits	-
Parity	None	-
Stop Bit	1 bit	-
Flow Control	None	-

7.2. I2C Communication Setting

Item	Setting Value	Notes
I2C Clock	400 kHz	In Master operation
Data Length	8 bits	-
Acknowledge	Available.	-
Start/Stop Condition	Generated.	-

7.3. SPI Communication Setting

Item	Setting Value	Notes
SPI Clock	24 MHz	-
Data Length	8 bits	-
Parity	None	-
Data Transfer Direction	MSB	-

7.4. EI2C

Item	Setting Value	Notes
Communication Speed	400kHz	

7.5. FUART

Item	Setting Value	Notes
Baud Rate	115200 bps	—
Data Length	8 bits	—
Parity	None	—
Stop Bit	1 bit	—
Flow Control	None	—

7.6. I2S

Item	Setting Value	Notes
Master Clock	1.548MHz	62 division
Bit Clock	1.548MHz	—

7.7. TSPI

Item	Setting Value	Notes
TSPI Clock	24MHz	—

7.8. TSSI

Item	Setting Value	Notes
Clock	1MHz	Frequency Divider=1/96 fixed

7.9. ETHM

Item	Setting Value	Notes
PHY Interface	MII Interface	—
Transfer Speed	10Mbps	—

8. Precautions for use

Please confirm the operation sufficiently if use in an environment other than the operation check environment.

9. Revision History

Revision	Date	Description
1.0	2021-11-25	First release

RESTRICTIONS ON PRODUCT USE

Toshiba Corporation and its subsidiaries and affiliates are collectively referred to as "TOSHIBA". Hardware, software and systems described in this document are collectively referred to as "Product".

- TOSHIBA reserves the right to make changes to the information in this document and related Product without notice.
- This document and any information herein may not be reproduced without prior written permission from TOSHIBA. Even with TOSHIBA's written permission, reproduction is permissible only if reproduction is without alteration/omission.
- Though TOSHIBA works continually to improve Product's quality and reliability, Product can malfunction or fail. Customers are responsible for complying with safety standards and for providing adequate designs and safeguards for their hardware, software and systems which minimize risk and avoid situations in which a malfunction or failure of Product could cause loss of human life, bodily injury or damage to property, including data loss or corruption. Before customers use the Product, create designs including the Product, or incorporate the Product into their own applications, customers must also refer to and comply with (a) the latest versions of all relevant TOSHIBA information, including without limitation, this document, the specifications, the data sheets and application notes for Product and the precautions and conditions set forth in the "TOSHIBA Semiconductor Reliability Handbook" and (b) the instructions for the application with which the Product will be used with or for. Customers are solely responsible for all aspects of their own product design or applications, including but not limited to (a) determining the appropriateness of the use of this Product in such design or applications; (b) evaluating and determining the applicability of any information contained in this document, or in charts, diagrams, programs, algorithms, sample application circuits, or any other referenced documents; and (c) validating all operating parameters for such designs and applications. **TOSHIBA ASSUMES NO LIABILITY FOR CUSTOMERS' PRODUCT DESIGN OR APPLICATIONS.**
- **PRODUCT IS NEITHER INTENDED NOR WARRANTED FOR USE IN EQUIPMENTS OR SYSTEMS THAT REQUIRE EXTRAORDINARILY HIGH LEVELS OF QUALITY AND/OR RELIABILITY, AND/OR A MALFUNCTION OR FAILURE OF WHICH MAY CAUSE LOSS OF HUMAN LIFE, BODILY INJURY, SERIOUS PROPERTY DAMAGE AND/OR SERIOUS PUBLIC IMPACT ("UNINTENDED USE").** Except for specific applications as expressly stated in this document, Unintended Use includes, without limitation, equipment used in nuclear facilities, equipment used in the aerospace industry, lifesaving and/or life supporting medical equipment, equipment used for automobiles, trains, ships and other transportation, traffic signaling equipment, equipment used to control combustions or explosions, safety devices, elevators and escalators, and devices related to power plant. **IF YOU USE PRODUCT FOR UNINTENDED USE, TOSHIBA ASSUMES NO LIABILITY FOR PRODUCT.** For details, please contact your TOSHIBA sales representative or contact us via our website.
- Do not disassemble, analyze, reverse-engineer, alter, modify, translate or copy Product, whether in whole or in part.
- Product shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable laws or regulations.
- The information contained herein is presented only as guidance for Product use. No responsibility is assumed by TOSHIBA for any infringement of patents or any other intellectual property rights of third parties that may result from the use of Product. No license to any intellectual property right is granted by this document, whether express or implied, by estoppel or otherwise.
- **ABSENT A WRITTEN SIGNED AGREEMENT, EXCEPT AS PROVIDED IN THE RELEVANT TERMS AND CONDITIONS OF SALE FOR PRODUCT, AND TO THE MAXIMUM EXTENT ALLOWABLE BY LAW, TOSHIBA (1) ASSUMES NO LIABILITY WHATSOEVER, INCLUDING WITHOUT LIMITATION, INDIRECT, CONSEQUENTIAL, SPECIAL, OR INCIDENTAL DAMAGES OR LOSS, INCLUDING WITHOUT LIMITATION, LOSS OF PROFITS, LOSS OF OPPORTUNITIES, BUSINESS INTERRUPTION AND LOSS OF DATA, AND (2) DISCLAIMS ANY AND ALL EXPRESS OR IMPLIED WARRANTIES AND CONDITIONS RELATED TO SALE, USE OF PRODUCT, OR INFORMATION, INCLUDING WARRANTIES OR CONDITIONS OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, ACCURACY OF INFORMATION, OR NONINFRINGEMENT.**
- Do not use or otherwise make available Product or related software or technology for any military purposes, including without limitation, for the design, development, use, stockpiling or manufacturing of nuclear, chemical, or biological weapons or missile technology products (mass destruction weapons). Product and related software and technology may be controlled under the applicable export laws and regulations including, without limitation, the Japanese Foreign Exchange and Foreign Trade Law and the U.S. Export Administration Regulations. Export and re-export of Product or related software or technology are strictly prohibited except in compliance with all applicable export laws and regulations.
- Please contact your TOSHIBA sales representative for details as to environmental matters such as the RoHS compatibility of Product. Please use Product in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive. **TOSHIBA ASSUMES NO LIABILITY FOR DAMAGES OR LOSSES OCCURRING AS A RESULT OF NONCOMPLIANCE WITH APPLICABLE LAWS AND REGULATIONS.**