

Item No.	Designator	Quantity	Value	Part Number	Manufacturer	Description	Package name	Standard dimensions mm (inch)	Not Mounted
1	IC303	1		DCL540C01	TOSHIBA	Digital Isolator	SOIC16-W		
2	IC403, IC451	2		TCR1HF50B	TOSHIBA	Regulator, 40V, V_OUT=5.0V	SOT-25 (SMV)		
3	IC1	1		HF81	MPS	X-CAP Bleeder			
4	IC51	1		UCC28070A	TI	PFC Controller			
5	IC151, IC201	2		UCC27524AD	TI	Gate Driver			
6	IC251	1		UCC28951	TI	PSFB Controller			
7	IC301, IC302	2		NJU7704F3-42A	Nisshinbo	Voltage Detector			
8	IC401	1		UCC28711DR	TI	Flyback Controller			
9	IC402	1		LM317MDCY	TI	Regulator			
10	IC501	1		LM74700-Q1	TI	ORing Controller			
11	Q151, Q152, Q153, Q154, Q155, Q156, Q201, Q202, Q203, Q204, Q205, Q206	12		TPW2900ENH	TOSHIBA	N-ch MOSFET, 200V, 30A	DSOP Advance		
12	Q301, Q351	2		SSM3K15AMFV	TOSHIBA	N-ch MOSFET, 30V, 100mA	SOT-723 (VESM)		
13	Q401	1		TK12A80W	TOSHIBA	N-ch MOSFET, 800V, 11.5A	TO-220SIS		
14	Q501, Q502, Q503, Q504, Q506, Q507	6		TPM1R908QM	TOSHIBA	N-ch MOSFET, 80V, 238A	SOP Advance(E)		
15	D1, D302	2		XCUZ5V6	TOSHIBA	Zener Diode, 5.6V, 0.2W	SOD-323 (USC)		
16	D2, D251	2		BAS316	TOSHIBA	Switching Diode, 100V, 0.25A	SOD-323 (USC)		
17	D51, D52, D53, D54	4		CRG04A	TOSHIBA	Rectification , 600V, 1A	S-FLAT		
18	D56	1		CRZ15	TOSHIBA	Zener Diode, 15V	S-FLAT		NOT MOUNT
19	D101, D102	2		TRS8E65H	TOSHIBA	SiC Barrier Diode, 650V, 8A	TO-220-2L		
20	D151, D152, D154, D155, D201, D202, D204, D205	8		CUHS15S30	TOSHIBA	Schottky Barrier Diode, 30V, 1.5A	SOD-323HE (US2H)		
21	D153, D156, D203, D206	4		TBAT54	TOSHIBA	Schottky Barrier Diode, 30V, 0.2A	SOT-23 (SOT23)		
22	D157, D158, D207, D208	4		CMH01	TOSHIBA	High Efficiency Diode, 200V, 3A	M-FLAT		
23	D303	1		1SS352	TOSHIBA	Switching Diode, 80V, 0.1A	SOD-323 (USC)		
24	D304	1		1SS405	TOSHIBA	Switching Diode, 20V, 0.05A	SOD-523 (ESC)		
25	D401	1		CRF03A	TOSHIBA	FRD, 600V, 0.7A	S-FLAT		
26	D402, D403	2		CRH01	TOSHIBA	High Efficiency Diode, 200V, 1A	S-FLAT		
27	D404	1		CRS01	TOSHIBA	Schottky Barrier Diode, 30V, 1A	S-FLAT		
28	D55	1		GSIB2580	Vishay	Bridge Rectifier, 800V, 3.5A			
29	D405	0		BAS316	TOSHIBA	Zener Diode, 15V	S-FLAT		NOT MOUNT
30	D451	1		RF501BGE2S	Rohm	FRD, 200V, 5A	D-PAK		
31	DS301	1		TLP385	TOSHIBA	Photocoupler, V _{CEO} =80V	4pin SO6L		

Item No.	Designator	Quantity	Value	Part Number	Manufacturer	Description	Package name	Standard dimensions mm (inch)	Not Mounted
32	R1, R2	2	75kΩ			500mW, ±1%		3.2 x 2.5 (1210)	
33	R3, R4	2	33Ω	Y5JA-330JPTL3.5	Uchihashi Estec	Thermal Fuse, 2.8W, ±5%			
34	R51, R52, R354, R357, R360, R363	6	1kΩ			63mW, ±5%		1.0 x 0.5 (0402)	
35	R53, R54, R55, R70, R71, R72	6	1MΩ			250mW, ±0.5%		3.2 x 1.6 (1206)	
36	R56, R73	2	1.2kΩ			63mW, ±0.5%		1.0 x 0.5 (0402)	
37	R57, R74, R280, R281	4	22kΩ			63mW, ±0.5%		1.0 x 0.5 (0402)	
38	R58, R313	2	47kΩ			63mW, ±5%		1.0 x 0.5 (0402)	
39	R59	1	47kΩ			63mW, ±1%		1.0 x 0.5 (0402)	
40	R60, R65	2	3.3kΩ			63mW, ±1%		1.0 x 0.5 (0402)	
41	R61, R258	2	33kΩ			63mW, ±1%		1.0 x 0.5 (0402)	
42	R62, R69	2	120kΩ			63mW, ±1%		1.0 x 0.5 (0402)	
43	R63	1	56kΩ			63mW, ±1%		1.0 x 0.5 (0402)	
44	R64, R151, R201, R416	4	1Ω			63mW, ±5%		1.0 x 0.5 (0402)	
45	R66	1	3.9kΩ			63mW, ±5%		1.0 x 0.5 (0402)	
46	R67, R68, R271	3	18kΩ			63mW, ±5%		1.0 x 0.5 (0402)	
47	R101, R102	2	300kΩ			1W, ±5%		6.3 x 3.2 (2412)	
48	R152, R155, R202, R205, R402	5	10Ω			250mW, ±5%		2.0 x 1.25 (0805)	
49	R153, R156, R203, R206, R504	5	3Ω			250mW, ±5%		2.0 x 1.25 (0805)	
50	R154, R157, R204, R207, R403	5	10kΩ			63mW, ±5%		1.0 x 0.5 (0402)	
51	R158, R208	2	100kΩ			250mW, ±1%		3.2 x 1.6 (1206)	
52	R159, R209	2	27kΩ			1W, ±5%		6.4 x 3.2 (2512)	
53	R160, R210	2	100kΩ			250mW, ±1%		3.2 x 1.6 (1206)	NOT MOUNT
54	R251	1	330Ω			250mW, ±5%		3.2 x 1.6 (1206)	
55	R252	1	13kΩ			63mW, ±1%		1.0 x 0.5 (0402)	
56	R253	1	15kΩ			63mW, ±1%		1.0 x 0.5 (0402)	
57	R254, R305	2	90kΩ			63mW, ±5%		1.0 x 0.5 (0402)	
58	R255	1	18kΩ			63mW, ±1%		1.0 x 0.5 (0402)	
59	R256, R408	2	22Ω			63mW, ±5%		1.0 x 0.5 (0402)	
60	R257	1	47kΩ			63mW, ±1%		1.0 x 0.5 (0402)	

Item No.	Designator	Quantity	Value	Part Number	Manufacturer	Description	Package name	Standard dimensions mm (inch)	Not Mounted
61	R259	1	12kΩ			63mW, ±1%		1.0 x 0.5 (0402)	
62	R260	1	220Ω			63mW, ±5%		1.0 x 0.5 (0402)	
63	R261, R264, R265	3	6.8kΩ			63mW, ±5%		1.0 x 0.5 (0402)	
64	R262, R263	2	6.8kΩ			63mW, ±5%		1.0 x 0.5 (0402)	NOT MOUNT
65	R266, R267, R417	3	2.2kΩ			63mW, ±1%		1.0 x 0.5 (0402)	
66	R268, R270, R312, R454, R505, R506	6	0Ω			1A		1.0 x 0.5 (0402)	
67	R269, R277	2	0Ω			1A		1.0 x 0.5 (0402)	NOT MOUNT
68	R272	1	430Ω			63mW, ±5%		1.0 x 0.5 (0402)	
69	R273	1	680Ω			63mW, ±5%		1.0 x 0.5 (0402)	
70	R274, R275, R276	3	33Ω			250mW, ±5%		3.2 x 1.6 (1206)	
71	R278	1	36kΩ			63mW, ±1%		1.0 x 0.5 (0402)	
72	R279	1	6.8kΩ			63mW, ±0.5%		1.0 x 0.5 (0402)	
73	R282	1	2.2kΩ			63mW, ±0.5%		1.0 x 0.5 (0402)	
74	R283, R414	2	470Ω			63mW, ±0.5%		1.0 x 0.5 (0402)	
75	R284	1	36Ω			250mW, ±5%		3.2 x 1.6 (1206)	NOT MOUNT
76	R301, R302, R303, R304, R309, R310, R311	7	1MΩ			250mW, ±5%		3.2 x 1.6 (1206)	
77	R306	1	12kΩ			63mW, ±5%		1.0 x 0.5 (0402)	
78	R307	1	680kΩ			63mW, ±1%		1.0 x 0.5 (0402)	
79	R308, R353	2	10Ω			63mW, ±5%		1.0 x 0.5 (0402)	
80	R314, R315, R351, R352	4	22kΩ			63mW, ±5%		1.0 x 0.5 (0402)	
81	R316	1	3.3kΩ			250mW, ±5%		3.2 x 1.6 (1206)	
82	R317	1	1.2kΩ			63mW, ±5%		1.0 x 0.5 (0402)	
83	R355, R358, R361, R364	4	4.7kΩ			63mW, ±5%		1.0 x 0.5 (0402)	
84	R356, R359, R362, R365	4	2.2kΩ			63mW, ±5%		1.0 x 0.5 (0402)	
85	R401	1	27kΩ	PR0300020 2702JAC00	Vishay	Metal Film, 3W, ±5%			
86	R404, R405, R406	3	1.2Ω			250mW, ±1%		3.2 x 1.6 (1206)	
87	R407	1	100kΩ			63mW, ±5%		1.0 x 0.5 (0402)	
88	R409	1	3.3kΩ			63mW, ±5%		1.0 x 0.5 (0402)	
89	R410	1	100kΩ			63mW, ±1%		1.0 x 0.5 (0402)	

Item No.	Designator	Quantity	Value	Part Number	Manufacturer	Description	Package name	Standard dimensions mm (inch)	Not Mounted
90	R411	1	22kΩ			63mW, ±1%		1.0 x 0.5 (0402)	
91	R412	1	33Ω			63mW, ±5%		1.0 x 0.5 (0402)	
92	R413	1	6.2kΩ			63mW, ±0.5%		1.0 x 0.5 (0402)	
93	R415, R453	2	100Ω			63mW, ±5%		1.0 x 0.5 (0402)	
94	R451	1	1.2kΩ			250mW, ±5%		3.2 x 1.6 (1206)	
95	R452	1	10mΩ	PMR18EZPFU10L0	Rohm	Metal Film, 1W, ±1%		3.2 x 1.6 (1206)	
96	R501	1	10kΩ			1W, ±5%		6.3 x 3.2 (2412)	
97	R502, R503	2	10kΩ			1W, ±5%		6.3 x 3.2 (2412)	NOT MOUNT
98	C1, C6	2	220nF	LE224-M	Okaya	Film, 275V, ±10%			
99	C2, C3	2	100pF	DE2B3SA101KA3BT02F	Murata	Ceramic, 250V, ±10%			
100	C4, C5, C7, C8	4	2.2nF	DE2E3SA222MN3AT02F	Murata	Ceramic, 250V, ±20%			
101	C9	1	2.2μF	890324026034CS	WURTH	Film, 275V, ±10%			
102	C11, C59, C153, C203, C252, C254, C411, C412, C413, C452, C453	11	1μF			Ceramic, 25V, ±20%		1.0 x 0.5 (0402)	
103	C51, C52, C53	3	1010μF	EKHE421VSN102MA45Z	CHEMI-CON	Aluminum, 420V, ±20%			
104	C54	1	220pF	DE2B3SA221KA3BT02F	Murata	Ceramic, 250V, ±10%			
105	C55, C56	2	2.2nF			Ceramic, 50V, ±10%		1.0 x 0.5 (0402)	
106	C57, C70	2	6.8nF			Ceramic, 50V, ±10%		1.0 x 0.5 (0402)	
107	C58, C256	2	3.3nF			Ceramic, 50V, ±10%		1.0 x 0.5 (0402)	
108	C60	1	22μF			Ceramic, 25V, ±20%		3.2 x 1.6 (1206)	
109	C61, C63, C253, C302, C305, C309, C310, C351, C509	8	100nF			Ceramic, 25V, ±10%		1.0 x 0.5 (0402)	
110	C62, C509	2	100nF			Ceramic, 25V, ±10%		1.0 x 0.5 (0402)	NOT MOUNT
111	C64, C66	2	150pF			Ceramic, 50V, ±5%		1.0 x 0.5 (0402)	
112	C65, C67, C255, C303, C306, C410	6	1nF			Ceramic, 50V, ±10%		1.0 x 0.5 (0402)	
113	C68	1	120nF			Ceramic, 25V, ±10%		1.6 x 0.8 (0603)	

Item No.	Designator	Quantity	Value	Part Number	Manufacturer	Description	Package name	Standard dimensions mm (inch)	Not Mounted
114	C69, C404	2	1.5 μ F			Ceramic, 35V, \pm 10%		2.0 x 1.25 (0805)	
115	C151, C152, C201, C202	4	10 μ F			Ceramic, 25V, \pm 10%		3.2 x 1.6 (1206)	
116	C258	1	10 μ F			Ceramic, 25V, \pm 10%		3.2 x 1.6 (1206)	NOT MOUNT
117	C154, C204,	2	330nF			Ceramic, 250V, \pm 10%		4.5 x 3.2 (1812)	
118	C155, C205	2	330nF			Ceramic, 250V, \pm 10%		4.5 x 3.2 (1812)	NOT MOUNT
119	C251	1	2.2 μ F			Ceramic, 25V, \pm 10%		2.0 x 1.25 (0805)	
120	C257	1	330pF			Ceramic, 50V, \pm 5%		1.0 x 0.5 (0402)	
121	C301	1	47nF			Ceramic, 630V, \pm 10%		3.2 x 1.6 (1206)	
122	C304	1	47nF			Ceramic, 50V, \pm 10%		1.0 x 0.5 (0402)	
123	C307	1	470nF			Ceramic, 50V, \pm 20%		1.0 x 0.5 (0402)	
124	C308	1	10nF			Ceramic, 50V, \pm 10%		1.0 x 0.5 (0402)	NOT MOUNT
125	C401	1	6.8 μ F	EKXJ451ELL6R8 MJ16S	CHEMI-CON	Aluminum, 450V, \pm 20%			
126	C402, C403	2	22nF			Ceramic, 630V, \pm 10%		3.2 x 1.6 (1206)	
127	C405, C406	2	150pF			Ceramic, 50V, \pm 5%		1.0 x 0.5 (0402)	NOT MOUNT
128	C407	1	470pF			Ceramic, 50V, \pm 5%		1.0 x 0.5 (0402)	
129	C408	1	330 μ F	EMLA350ARA331 MJA0G	CHEMI-CON	Aluminum, 35V, \pm 20%			
130	C409	1	2.2nF			Ceramic, 50V, \pm 10%		1.0 x 0.5 (0402)	NOT MOUNT
131	C414	1	470pF	DE2B3SA471KA3 BT02F	Murata	Ceramic, 250V, \pm 10%			
132	C451	1	1200 μ F	EKZN250ELL122 MJ25S	CHEMI-CON	Aluminum, 25V, \pm 20%			
133	C501, C502, C503	3	330 μ F	EKZN630ELL331 MJ25S	CHEMI-CON	Aluminum, 63V, \pm 20%			
134	C504, C507, C508, C510, C511	5	33nF			Ceramic, 100V, \pm 5%		2.0 x 1.25 (0805)	
135	C505, C506	2	1 μ F			Ceramic, 100V, \pm 10%		2.0 x 1.25 (0805)	
136	L1, L2	2	8.1mH	LDFW021252YB UV0E	CHEMI-CON	Choke Coils, 21A			
137	L51, L52	2	100 μ H	TAM-30A131	TAMURA	Choke Coils, 30A			
138	L101	1	13 μ H	08C25178	CPE	Choke Coils			
139	L151, L201	2	9.5 μ H	TAM-CTW32A6R5	TAMURA	Choke Coils, 32A			
140	T101	1		PE-63587	PULSE	Transformer			
141	T151, T201	2		TAM-PQ40-16-3	TAMURA	Transformer			
142	T401	1		TAM-PQ20-36-5	TAMURA	Transformer			

Item No.	Designator	Quantity	Value	Part Number	Manufacturer	Description	Package name	Standard dimensions mm (inch)	Not Mounted
143	F1	1		0326030.MXP	Littelfuse	Ceramic Fuse, 30A			
144	F401	1		80812000440	Littelfuse	Fuse			
145	RV1	1	560VΩ	TND14V-561KB00AAA0	CHEMI-CON	Ceramic Varistor			
146	RY1	1		G2RL-1A-E2-CV-HA_DC12	OMRON	Relay			
147	CN1	1		B3P-VH	JST	Connector, 3 Position			
148	CN501	1		B4B-XH-A	JST	Connector, 4 Position			
149	CN502	1		B2B-XH-A(LF)(SN)	JST	Connector, 2 Position			
150	DP55	1		LC-22-S-WHITE	MAC8	Test Pin			
151	DP56, DP157, DP207, DP252, DP253, DP254, DP255, DP256, DP257, DP501, DP502, DP503	12		HK-2-S	MAC8	Test Pin			
152	DP258	1		LC-22-S-BLACK	MAC8	Test Pin			
153	TB1	1		OTB-780N-B-3P-M4	OSADA	Terminal			
154	TB501, TB502	2		7460305	WURTH	Terminal			
155	FH1, FH2	2		01220083Z	Littelfuse	Fuse Holder			

Terms of Use

This terms of use is made between Toshiba Electronic Devices and Storage Corporation ("We") and Customer who downloads or uses this Reference Design. Customer shall comply with this terms of use. This Reference Design means all documents and data in order to design electronics applications on which our semiconductor device is embedded.

Section 1. Restrictions on usage

1. This Reference Design is provided solely as reference data for designing electronics applications. Customer shall not use this Reference Design for any other purpose, including without limitation, verification of reliability.
2. Customer shall not use this Reference Design for sale, lease or other transfer.
3. Customer shall not use this Reference Design for evaluation in high or low temperature, high humidity, or high electromagnetic environments.
4. This Reference Design shall not be used for or incorporated into any product or system whose manufacture, use, or sale is prohibited under any applicable laws or regulations.

Section 2. Limitations

1. We reserve the right to make changes to this Reference Design without notice.
2. This Reference Design should be treated as a reference only. WE ARE NOT RESPONSIBLE FOR ANY INCORRECT OR INCOMPLETE DATA AND INFORMATION.
3. Semiconductor devices can malfunction or fail. When designing electronics applications by referring to this Reference Design, Customer is responsible for complying with safety standards and for providing adequate designs and safeguards for their hardware, software and systems which minimize risk and avoid situations in which a malfunction or failure of semiconductor devices could cause loss of human life, bodily injury or damage to property, including data loss or corruption. Customer must also refer to and comply with the latest versions of all relevant our information, including without limitation, specifications, data sheets and application notes for semiconductor devices, as well as the precautions and conditions set forth in the "Semiconductor Reliability Handbook".
4. Designing electronics applications by referring to this Reference Design, Customer must evaluate the whole system sufficiently. Customer is solely responsible for applying this Reference Design to Customer's own product design or applications. WE ASSUME NO LIABILITY FOR CUSTOMER'S PRODUCT DESIGN OR APPLICATIONS.
5. WE SHALL NOT BE RESPONSIBLE FOR ANY INFRINGEMENT OF PATENTS OR ANY OTHER INTELLECTUAL PROPERTY RIGHTS OF THIRD PARTIES THAT MAY RESULT FROM THE USE OF THIS REFERENCE DESIGN. NO LICENSE TO ANY INTELLECTUAL PROPERTY RIGHT IS GRANTED BY THIS TERMS OF USE, WHETHER EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE.
6. THIS REFERENCE DESIGN IS PROVIDED "AS IS". WE (a) ASSUME NO LIABILITY WHATSOEVER, INCLUDING WITHOUT LIMITATION, INDIRECT, CONSEQUENTIAL, SPECIAL, OR INCIDENTAL DAMAGES OR LOSS, INCLUDING WITHOUT LIMITATION, LOSS OF PROFITS, LOSS OF OPPORTUNITIES, BUSINESS INTERRUPTION AND LOSS OF DATA, AND (b) DISCLAIM ANY AND ALL EXPRESS OR IMPLIED WARRANTIES AND CONDITIONS RELATED TO THIS REFERENCE DESIGN, INCLUDING WITHOUT LIMITATION, WARRANTIES OR CONDITIONS OF FUNCTION AND WORKING, WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, ACCURACY OF INFORMATION, OR NONINFRINGEMENT.

Section 3. Terms and Termination

It is assumed that Customer agrees to any and all this terms of use if Customer downloads or uses this Reference Design. We may, at its sole and exclusive discretion, change, alter, modify, add, and/or remove any part of this terms of use at any time without any prior notice. We may terminate this terms of use at any time and without any cause. Upon termination of this terms of use, Customer shall eliminate this Reference Design. Furthermore, upon our request, Customer shall submit to us a written confirmation to prove elimination of this Reference Design.

Section 4. Export Control

Customer shall not use or otherwise make available this Reference Design for any military purposes, including without limitation, for the design, development, use, stockpiling or manufacturing of nuclear, chemical, or biological weapons or missile technology products (mass destruction weapons). This Reference Design may be controlled under the applicable export laws and regulations including, without limitation, the Japanese Foreign Exchange and Foreign Trade Act and the U.S. Export Administration Regulations. Export and re-export of this Reference Design is strictly prohibited except in compliance with all applicable export laws and regulations.

Section 5. Governing Laws

This terms of use shall be governed and construed by laws of Japan, without reference to conflict of law principle.

Section 6. Jurisdiction

Unless otherwise specified, Tokyo District Court in Tokyo, Japan shall be exclusively the court of first jurisdiction for all disputes under this terms of use.

ご利用規約

本規約は、お客様と東芝デバイス&ストレージ株式会社（以下「当社」といいます）との間で、当社半導体製品を搭載した機器を設計する際に参考となるドキュメント及びデータ（以下「本リファレンスデザイン」といいます）の使用に関する条件を定めるものです。お客様は本規約を遵守しなければなりません。

第1条 禁止事項

お客様の禁止事項は、以下の通りです。

1. 本リファレンスデザインは、機器設計の参考データとして使用されることを意図しています。信頼性検証など、それ以外の目的には使用しないでください。
2. 本リファレンスデザインを販売、譲渡、貸与等しないでください。
3. 本リファレンスデザインは、高温・多湿・強電磁界などの対環境評価には使用できません。
4. 本リファレンスデザインを、国内外の法令、規則及び命令により、製造、使用、販売を禁止されている製品に使用しないでください。

第2条 保証制限等

1. 本リファレンスデザインは、技術の進歩などにより予告なしに変更されることがあります。
2. 本リファレンスデザインは参考用のデータです。当社は、データ及び情報の正確性、完全性に関して一切の保証をいたしません。
3. 半導体素子は誤作動したり故障したりすることがあります。本リファレンスデザインを参考に機器設計を行う場合は、誤作動や故障により生命・身体・財産が侵害されることのないように、お客様の責任において、お客様のハードウェア・ソフトウェア・システムに必要な安全設計を行うことをお願いします。また、使用されている半導体素子に関する最新の情報（半導体信頼性ハンドブック、仕様書、データシート、アプリケーションノートなど）をご確認の上、これに従ってください。
4. 本リファレンスデザインを参考に機器設計を行う場合は、システム全体で十分に評価し、お客様の責任において適用可否を判断して下さい。当社は、適用可否に対する責任を負いません。
5. 本リファレンスデザインは、その使用に際して当社及び第三者の知的財産権その他の権利に対する保証又は実施権の許諾を行うものではありません。
6. 当社は、本リファレンスデザインに関して、明示的にも黙示的にも一切の保証（機能動作の保証、商品性の保証、特定目的への合致の保証、情報の正確性の保証、第三者の権利の非侵害保証を含むがこれに限らない。）をせず、また当社は、本リファレンスデザインに関する一切の損害（間接損害、結果的損害、特別損害、付随的損害、逸失利益、機会損失、休業損害、データ喪失等を含むがこれに限らない。）につき一切の責任を負いません。

第3条 契約期間

本リファレンスデザインをダウンロード又は使用することをもって、お客様は本規約に同意したものとみなされます。本規約は予告なしに変更される場合があります。当社は、理由の如何を問わずいつでも本規約を解除することができます。本規約が解除された場合は、お客様は本リファレンスデザインを破棄しなければなりません。さらに当社が要求した場合には、お客様は破棄したことを証する書面を当社に提出しなければなりません。

第4条 輸出管理

お客様は本リファレンスデザインを、大量破壊兵器の開発等の目的、軍事利用の目的、あるいはその他軍事用途の目的で使用してはなりません。また、お客様は「外国為替及び外国貿易法」、「米国輸出管理規則」等、適用ある輸出関連法令を遵守しなければなりません。

第5条 準拠法

本規約の準拠法は日本法とします。

第6条 管轄裁判所

本リファレンスデザインに関する全ての紛争については、別段の定めがない限り東京地方裁判所を第一審の専属管轄裁判所とします。